

Remarks/Arguments

Objection to the Drawings

The Examiner has objected to the drawings. In response, Applicant submits marked-up drawings with the changes suggested by the Examiner. The label of Fig. 1 has been changed to "Prior Art." Figure 3 has been changed to indicate that the switches S, S1 are in their non-conductive state as described on page 6, lines 1-3. Figure 4 has been changed to indicate that the switches S, S1 are in their conductive state as described on page 6, lines 16-17.

Objection to the Specification

The Examiner has objected to the specification because of lack of headings and because of mislabeled elements. Applicant submits a substitute specification with headings and with correct labeling of transmission coil L1 (page 2, line 16) and further switching means S1 (page 5, line 29). Additionally, on page 2, line 3, "record carrier" has been changed to -- data carrier -- and on page 7, line 17, "van" has been changed to -- can --.

Claim Objections

Claims 1-5 are pending in the application. Claims 1-5 are rejected.

Claims 1-5 have been objected to because of an informality in claim 1. Claim 1 has been amended to overcome the objection.

Claims 3-4 have been objected to as being of improper dependent form for failing to further limit the subject matter of the previous claim. The Examiner states that the limitation recited in claim 3 regarding controlling the capacitance value of the capacitor configuration has been recited in claim 2. Applicant respectfully requests that the Examiner reconsider this objection. Page 3, line 28 of the specification describes that the capacitor configuration can be controlled in different manners. Claim 2 recites that between the two elements of the second transmission coil and capacitor configuration only the capacitor configuration is configured to be

controllable as regards its capacitance value. However, claim 2 leaves open that the capacitor configuration may also be configured in a different manner. Claim 3 further limits claim 2 by reciting that the capacitor configuration is configured to be controllable only (emphasis added) as regards its capacitance value. Therefore, Applicant respectfully requests that the Examiner withdraw the objection to claims 3 and 4.

Claim Rejections Under 35 USC § 112

Claims 1-5 are rejected under 35 U.S.C. 112, first paragraph as failing to comply with the enabling requirement. The Examiner states that the language of claim 1 is exactly opposite to the teaching of the specification. The Examiner states that claim 1 recites that the switching means (S) is in its conductive switching state during a communication process but that the specification (page 6, lines 1-3) states that the switch is set to the non-conductive switching state at communication mode. It appears that the Examiner has interpreted "communication process" and "communication mode" to be the same. However, the data carrier (DC) may conduct a communication process when the switch is in either communication mode or rest mode. A communication process takes place with the aid of a carrier signal (CS) (page 4, lines 33-34). As seen in the drawings, the data carrier (DC) may receive a carrier signal (CS) during a communication process when the switch is set to communication mode (Fig. 3) or rest mode (Fig. 4). Claim 1 recites a first transmission coil through which a coil current (I1) flows during a communication process during which the switching means (S) is in its conductive switching state (i.e., the rest mode of Fig. 4). Therefore, Applicant believes that this recitation in claim 1 conforms to the specification.

The Examiner further states that recitation in claim 1 of phase lag (line 11) and phase lead (line 17) should occur at rest mode. Applicant submits that the recitation of claim 1 is correct. Claim 1 recites that the phase lag and phase lead occur when the switching means (S)

is in its conductive state (rest mode). This is as described in the specification on page 6, lines 29-35.

The Examiner goes on to state that the claimed limitation in the last three lines of claim 1 cover three different situations but that the specification only supports controlling the value of the capacitor configuration (CC). However, page 3, lines 5-8 of the specification recites that the value of all of the elements of the receiving means may be controlled. Therefore, Applicant submits that claim 1 is enabled by the specification and respectfully requests that the rejection under 35 U.S.C. 112, first paragraph, be withdrawn.

Claim Rejections Under 35 USC § 102

Claims 1 and 5 are rejected under 35 USC 102(e) as being anticipated by Trontelj (US Patent No. 6,208,235). A claim is anticipated only if each and every element as set forth in the claim is found, either expressly or inherently described, in a single prior art reference. *Verdegaal Bros. v. Union Oil Co. of California*, 814 F.2d 628, 631, 2 USPQ2d 1051, 1053 (Fed. Cir. 1987). Claim 1 recites a capacitor configuration (CC) arranged in parallel with at least one second transmission coil (L2). The Examiner states that Trontelj teaches a capacitor configuration (24 in Fig. 1) arranged in parallel with at least one second transmission coil (22 in Fig. 1). However, the Examiner's attention is directed to column 4, lines 44-45, of Trontelj where it is described that coil 22 is electrically connected with a capacitive element or resonant capacitor 24 in a series (emphasis added) loop. Therefore, Trontelj does not anticipate claim 1.

The present invention is directed to a data carrier in which the receiving means configuration (RC) is controlled by a switching arrangement so that during a rest mode (when the switches S and S1 are closed or in the conductive state) the two coils L1 and L2 produce magnetic fields that cancel each other so that the data carrier (DC) produces no undesired influence on a directly adjacent data carrier. Prior art devices are known to comprise two coils

and a capacitor arranged with the aim being that the magnetic fields produced by two coils cancel each other in a selected mode. However, because the two coils and capacitor of prior art designs have fixed values it is substantially impossible to obtain currents through the two coils which produce magnetic fields that cancel each other. The present invention overcomes this difficulty by providing a switching arrangement that controls the value of at least one element of the receiving means configuration (RC) as is now recited in Claim 1. Trontelj discloses controlling the values of the first and second coils by adjusting the number, size, and relative placement of the turns of the coils (column 7, lines 48-53). Trontelj does not disclose controlling the value of one of the elements of the receiving means configuration (RC) as recited in claim 1.

Additionally, the Office Action fails to meet the requirements of MPEP § 707.07(d): "Where a claim is refused the ground of rejection [should be] fully and clearly stated." The Examiner did not address the status of claims 2-4 based on prior art. Applicant is therefore unable to respond to the rejection because no reference has been made to anything in Trontelj that specifically corresponds to claims 2-4.


In view of the foregoing reasons for distinguishing over the cited references, Applicant has not raised other possible grounds for traversing the rejections, and therefore nothing herein should be deemed as acquiescence in any rejection or waiver of arguments not expressed herein.

CONCLUSION

Applicant submits that in view of the foregoing remarks and/or amendments, the application is in condition for allowance, and favorable action is respectfully requested. The Commissioner is hereby authorized to charge any fees, including extension fees, which may be required, or credit any overpayments, to Deposit Account No. 50-1001.

Respectfully submitted,

Date: September 7, 2004



James L. Wolfe
Registration No. 33,623
P. O. Box 10105
Portland, Oregon 97296
Telephone: (503) 224-2713
Facsimile: (503) 296-2172
Email: mail@ganzlaw.com

Correspondence to:

Philips Intellectual Property & Standards
1109 McKay Drive; Mail Stop SJ41
San Jose, CA 95131 USA
Telephone: (408) 474-9073
Facsimile: (408) 474-9082
USPTO Customer Number: 24738

DATA CARRIER HAVING A CONTROLLABLE CARRIER-SIGNAL RECEIVING - MEANS CONFIGURATION

~~Data carrier having a controllable carrier-signal-receiving-means-configuration~~

5 BACKGROUND OF THE INVENTION

The invention relates to a data carrier which is configured to communicate with a communication station with the aid of a carrier signal and which includes a receiving-means configuration having a switching means and having a first transmission coil that can be short-circuited and having a second transmission coil and having a capacitor configuration.

10 Such a data carrier is commercially available and is consequently known. The construction of the relevant part of the known data carrier is shown in Fig. 1.

The known data carrier DC includes a receiving-means configuration RC and a chip CH connected to the receiving-means configuration RC. The receiving-means configuration RC includes a switching means S, a first transmission coil L1 that can be short-circuited with the aid of the switching
15 means S, a second transmission coil L2 arranged in series with the first transmission coil L1, and a capacitor configuration CC arranged in parallel with the series arrangement of the first transmission coil L1 and the second transmission coil L2. The capacitor configuration CC now consists of a capacitor C external to the chip CH and of the input capacitance of the chip CH, but this is shown as a single capacitor C in an equivalent diagram. The switching means S is switchable between a
20 conductive switching state and a non-conductive switching state. The switching means S can be changed over with the aid of control means CM, which are incorporated in the chip CH and which are connected to the switching means S via a control line CL.

In a mode of communication between the data carrier DC and a communication station the switching means S is in its non-conductive switching state, as a result of which the two transmission
25 coils L1 and L2 are arranged in series and this series arrangement of the two transmission coils L1 and L2 is arranged in parallel with the capacitor configuration CC. The two transmission coils L1 and L2 then have an inductance value and the capacitor configuration CC has a capacitance value, which

inductance value and which capacitance value are selected in such a manner that the resonant circuit formed by the two transmission coils L1 and L2 and the capacitor configuration CC has a resonant frequency which corresponds to the carrier signal frequency f_c of the carrier signal CS used in the communication process.

5 In a rest mode of the ~~reced~~ data carrier DC, when the data carrier DC is not in a mode in which it communicates with a communication station, free switching means S is in its conductive state. When in this operating mode of the data carrier DC, i.e. in its rest mode, the data carrier DC enters into communication with a communication station, this results in a coil current I1 through the first transmission coil L1, which is an inductive coil current having a phase lag with respect to the
10 voltage across the first transmission coil L1. Furthermore, it results in a coil current I2 through the second transmission coil L2, i.e. a capacitive coil current having a phase lead with respect to the voltage across the second transmission coil L2. Each of these two coil currents I1 and I2 produces a magnetic field with the aid of the respective coil L1 or L2, which two magnetic fields attenuate one another, the aim being that the two magnetic fields cancel one another, so that owing to the desired
15 cancellation of the two magnetic fields free data carrier DC cannot have any adverse effect on the transmission coil of a nearby data carrier.

Owing to the selected design, which uses two fixed-value transmission coils [L] L1 and L2 and a fixed-value capacitor configuration, which elements always exhibit a spread in value, it is substantially impossible with the known data carrier DC to obtain currents I1 and I2 through the two
20 transmission coils L1 and L2 which cause magnetic fields which cancel one another. Thus, with the known data carrier DC the two transmission coils L1 and L2 always produce a residual magnetic field when the data carrier DC is in its rest mode, in which the switching means S is in its conductive state, as a result of which the residual magnetic field exerts an undesired influence on a nearby data carrier, which undesired influence results in the resonant frequency f_r no longer corresponding to the carrier
25 signal frequency f_c , as a result of which the receiving means configuration RC of the nearby data carrier DC does not guarantee a correct reception of a carrier signal CS and, consequently, the

generation of energy from the received carrier signal CS is not satisfactory, which leads to a distinct reduction of the range of a nearby data carrier DC when the nearby data carrier is set to its communication state, i.e. a communication mode, in which the switching means S of the nearby data carrier is set to its non-conductive state.

5 BRIEF SUMMARY OF THE INVENTION

It is an object of the invention to preclude the afore-mentioned problems and to provide simple and effective means in a data carrier of the type defined in the opening paragraph, by which means an improved data carrier is obtained.

10 In order to achieve this object with such a data carrier the receiving means configuration is configured to be controllable as regards the value of at least one of its elements comprising the at least one second transmission coil and the capacitor configuration.

In this way, it is achieved by simple means that by switching the value of the at least one second transmission coil or of the capacitor configuration, or also of all these elements of the receiving means, it is possible to obtain a coil current in the second transmission coil of a data carrier in
15 accordance with the invention, which crescent leads with respect to the voltage across the second transmission coil and which by means of the second transmission coil produces a magnetic field whose magnitude corresponds exactly to the magnetic field produced by means of the first transmission coil but which is exactly phase-invoked with respect to this magnetic field, as a result of which the magnetic fields generated by means of the two transmission coils cancel one another almost
20 completely, so that in the rest mode of the data carrier in accordance with the invention, in which the switching means are in the conductive state, there is hardly any residual magnetic field and, consequently, a record carrier in accordance with the invention cannot exert a negative influence on a data carrier disposed near the data carrier in accordance with the invention. Thus, with a data carrier in accordance with the invention it is achieved in a simple manner that a data carrier in accordance with
25 the invention cannot cause a shift in the resonant frequency of the receiving means of a nearby data carrier when the nearby data carrier is in its communication mode, as a result of which a data carrier in

the proximity of a data carrier in accordance with the invention can communicate correctly without its range being limited, in spite of the immediate proximity of a data carrier in accordance with the invention.

It has proved to be very advantageous in a data carder in accordance with the invention if the capacitor configuration is configured to be controllable only as regards its capacitance value. This has proved to be advantageous in view of a simple realization and in view of a large number of control possibilities.

The capacitor configuration can be controlled in different manners, particularly if the capacitor configuration is realized with the aid of the chip connected to the receiving means configuration.

However, it has proved to be particularly advantageous if controlling is effected by switching over, i.e. if the capacitor configuration is switchable as regards its capacitance value. This is particularly advantageous in conjunction with an implementation by means of integrated circuit technology.

In the present context it has further proved to be very advantageous if a data carrier having a switchable capacitor configuration in addition has the characteristic features as defined in claim 4.

Such a construction has proved to be advantageous in view of an embodiment which is as simple as possible and which can be realized by means of integrated circuit technology. In such an embodiment a plurality of capacitors having fixed capacitance can be arranged in parallel with the series arrangement of a further capacitor and a further switching means.

In a data carrier in accordance with the invention the capacitor configuration may be arranged in parallel with the series arrangement of the two transmission coils. However, it has proved to be particularly advantageous if the capacitor configuration is arranged in parallel only with the at least one second transmission coil. Such an embodiment has proved to be very advantageous in practical tests.

The above-mentioned as well as further aspects of the invention will become apparent from the embodiments described hereinafter by way of example and will be elucidated with reference to these examples.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention will now be described in more detail with reference to the drawings, which show two embodiments given by way of example but to which the invention is not limited.

Fig. 1 is a block diagram which shows a prior-art data carrier.

5 Fig. 2 shows, in a manner similar to Fig. 1, a data carrier in accordance with a first embodiment of the invention.

Fig. 3 shows an equivalent diagram of the data carrier shown in Fig. 2, namely for the mode of operation in which the data carrier is in a mode of communication with a communication station.

10 Fig. 4 shows, in a manner similar to Fig. 3, an equivalent diagram of the data carrier shown in Fig. 2, namely for the mode of operation in which the data carrier is in a rest mode.

Fig. 5 shows, in a manner similar to Fig. 2, a data carrier in accordance with a second embodiment of the invention.

DETAILED DESCRIPTION OF THE INVENTION

15 Fig. 2 shows a data carrier in accordance with a first embodiment of the invention. The data carrier DC is configured to communicate with a communication station, not shown, with the aid of a carrier signal CS having a given carrier signal frequency f_c . The data carrier DC includes a receiving-means configuration RC, which serves for receiving the carrier signal CS in a mode of the data carrier DC in which it communicates with a communication station. The receiving-means configuration RC is connected to a chip CH of the data carrier DC. The receiving-means configuration RC has a plurality
20 of parts, which will be described in greater detail hereinafter.

The receiving-means configuration RC includes a switching means S, which formed by an electronic switch and which can be switched between a conductive switching state and a non-conductive switching state. To control or switch the switching means S the chip CH includes control means CM, which are connected to the switching means S via a control line CL.

25 The receiving means configuration RC further include a first transmission coil L1, which can be short-circuited with the aid of the switching means S.

The receiving means configuration RC further include a second transmission coil L2 arranged in series with the first transmission coil L1. It is also possible to provide more than two transmission coils, in which case at least one of these coils must be controllable or switchable as regards its value. In the present case the two transmission coils L1 and L2 are arranged in the receiving-means configuration RC with opposite winding directions. However, this is not necessary, the two transmission coils L1 and L2 may alternatively be included in the receiving-means configuration RC with the same winding direction.

The receiving-means configuration RC further includes a capacitor configuration CC which, in the present case, is arranged in parallel with the second transmission coil L2 only. In this case, the capacitor configuration CC is advantageously controllable as regards its capacitance value, the control capability in the present case being a switching capability. The capacitor configuration CC includes a capacitor C and, connected in parallel with the capacitor C, a series arrangement of a further capacitor C1 and a further switching means S1. The further switching means S1 is also formed by an electronic switch and is switchable between a conductive switching state and a non-conductive switching state. In order to enable it to be switched over the further switching means S is connected, in a manner similar to the switching means S, to the further control means CM via a further control line CL1. It is to be noted that in the present case the capacitor configuration CC is arranged in parallel with the second transmission coil L2 only and is consequently arranged in series with the first transmission coil L1, which is connected in series with the second transmission coil L2.

When the data carrier DC is set or switched to its communication mode as illustrated in Fig. 2, the switching means S and the further switching means SI are set to their non-conductive switching states, which results in the equivalent diagram shown in Fig. 3 for the data carrier DC shown in Fig. 2. As is apparent from Fig. 3, only the second transmission coil L2 and the capacitor configuration CC are active when the communication mode is active. The inductance value of the second transmission coil L2 and the capacitance value of the capacitor configuration CC in the data carrier DC shown in Fig. 2 is selected so as to obtain for the parallel resonant circuit formed by the second transmission

coil L2 and the capacitor configuration CC a resonant frequency f_R which corresponds to the carrier signal frequency f_C of the carrier signal CS transmitted by a communication station and received by the data carrier DC. This guarantees an optimum power generation in the data carrier DC with the aid of the received carrier signal CS and a correct data transfer between the communication station and the data carrier DC.

The data carrier DC shown in Fig. 2 can be set or switched not only to a communication mode (see Fig. 3) but also to a rest mode, which will be explained with respect to Fig. 4. In the rest mode the switching means S and the further switching means S1 are each set or switched to their conductive switching states, namely with the aid of the control means CM. This results in the equivalent diagram of Fig. 4 for the rest mode. In this rest mode the situation may arise that the data carrier DC is within a range of communication with a communication station although no communication is required between the data carrier DC and the communication station. This may be the case, for example, when a plurality of data carriers in accordance with the invention are disposed or arranged directly adjacent one another, of which plurality of data carriers which are arranged directly adjacent one another always only one data carrier DC should or is allowed to be in communication with the communication station. This operational situation may arise, for example, when a data carrier DC in accordance with the invention is attached to a sheet of paper, the sheets which each have a data carrier DC in accordance with the invention attached to it being stacked onto one another.

When a data carrier DC, when in its rest mode, in which the switching means S and the further switching means S1 are in their conductive switching states, is within a range of communication with a communication station, this results in a coil current I1 through the transmission coil L1, which current has a phase lag with respect to the voltage U1 across the first transmission coil L1, and in a coil current I2 through the second transmission coil L2, which current has a phase lead with respect to the voltage U2 across the second transmission coil L2. The lagging coil current I1 is an inductive current and the leading coil current I2 is a capacitive current. The lagging coil current I1 through the transmission coil L1 and the coil current I2 through the second transmission coil L2 produce two

magnetic fields, which cancel one another owing to the choice of the inductance values of the two transmission coils L1 and L2 and owing to the choice of the capacitance values of the capacitors C and C1, as a result of which in the rest mode (see Fig. 4) of the data carrier DC no residual magnetic fields are produced by the data carrier DC, which ensures that the data carrier DC cannot exert an undesired influence on a directly adjacent data carrier by means of a spuriously emitted residual magnetic field.

Fig. 5 shows a data carrier DC in accordance with a second embodiment of the invention. The data carrier shown in Fig. 5 differs from the data carrier DC shown in Fig. 2 in that the capacitor configuration CC is arranged not only in parallel with the second transmission coil L2 but the capacitor configuration CC is also arranged in parallel with the series arrangement of the first transmission coil L1 and the second transmission coil L2.

Both with the data carrier DC shown in Fig. 2 and with the data carrier DC shown in Fig. 5 it is achieved in a simple and very reliable manner and by simple means that in the rest mode of each of these data carriers DC no undesired residual magnetic fields [van] can be generated or caused by means of the transmission coils L1 and L2 of these data carriers DC, as a result of which the data carriers DC in accordance with the invention correct exert any undesired influences caused by the data carriers DC in accordance with the invention on data carriers disposed directly adjacent a data carrier DC in accordance with the invention.

It is to be noted that the switching means S and S1 and the capacitors C and C1 can also be realized by means of the chip CH, i.e. internally in the chip.

In a possible modification of a data carrier in accordance with the invention the capacitor C may be arranged only in parallel with the second transmission coil L2 of the series arrangement of the two transmission coils L1 and L2 and the second capacitor C1. It is also possible, to arrange the further capacitor C1 only in parallel with the second transmission coil L2 of the series arrangement of the two transmission coils L1 and L2 and the capacitor C.